

(Following Paper ID and Roll No. to be filled in your
Answer Books)

Paper ID : 131602

Roll No.

--	--	--	--	--	--	--	--	--	--

B.TECH.

Theory Examination (Semester-VI) 2015-16

DIGITAL SIGNAL PROCESSING

Time : 3 Hours

Max. Marks : 100

Section-A

Q1. Attempt all question.

(2×10=20)

- (a) Define DSP and its applications.
- (b) Define computational efficiency of FFT.
- (c) What are Gibbs Oscillations?
- (d) What substitution is made in place of s in case of bilinear transformation?
- (e) Write the time reversal and circular frequency shift property of DFT.
- (f) Write the relationship between DFT and Z transform.

- (g) Write five differences between Analog and Digital filters.
- (h) Write five differences between IIR and FIR filters.
- (i) Find the linear convolution of $S_1(n) = (1, 2, 3, 4)$ and $S_2(n) = (2, 3, 2, 1)$
- (j) What is linear phase FIR Filter?

Section-B

Q2. Attempt any five questions.

(10×5=50)

- (a) Determine $H(z)$ using the impulse invariant technique for the analog system function :

$$H(s) = \frac{1}{(s + 0.5)(s^2 + 0.5s + 2)}$$

- (b) Define DSP. Draw the block diagram of DSP and explain its components.
- (c) Calculate the product of the DFT's of the two sequences $s_1(n)$ and $s_2(n)$, where $s_1(n) = \{ 1, 1, 1, 1 \}$ and $s_2(n) = \{ 1, 2, 1, 2 \}$
- (d) Realise an FIR filter whose impulse response is $h(n) = \{ 2, 5, 6, 3, 6, 5, 2 \}$

(e) Drive and draw the butterfly diagram for DIFFFT for $N = 8$

(f) Given the system function $H(z) = \frac{2 + 8z^{-1} + 6z^{-2}}{1 + 8z^{-1} + 12z^{-2}}$.

Realise it using ladder structure.

Section-C

Attempt any two questions.

(15×2=30)

Q3. Given $x(n) = 2^n$ and $N=8$ find $X(K)$ using DIT FFT algorithm. Also calculate the computational reduction factor. Explain frequency transformation with LPF to HPF conversion formula.

Q4. (i) Determine the response of a discrete-time system to input signal $s(n) = \{2, 1, 3, 1\}$, if the unit-sample response is of the system is $h(n) = \{1, 2, 2, -1\}$

(ii) The desired response of a low-pass filter is

$$H_d(e^{j\omega}) = \begin{cases} e^{-j3\omega}, & -\frac{3\pi}{4} \leq \omega \leq \frac{3\pi}{4} \\ 0, & \frac{3\pi}{4} < |\omega| < \pi \end{cases}$$

Determine $H(e^{j\omega})$ for $M=7$ using a hamming window.

Q5. Design a digital chebyshev filter to satisfy the constraints :

$$0.707 \leq |H(e^{j\omega})| \leq 1 \quad 0 \leq \omega \leq 0.2\pi \quad \text{Using bilinear transformation with } T=1\text{s}$$

$$|H(e^{j\omega})| \leq 0.1, \quad 0.5\pi \leq \omega \leq \pi$$

